

# AMPERES CM-1400

## CHIME AND SIREN TONE GENERATOR



### INTRODUCTION

**CM1400** offers 5 chimes and 2 siren tones with selectable balanced and unbalanced line output. Activation of chime shall be from front switches or via remote triggering terminal, enabling the unit to be linked to external sensor or triggering system such as alarm panel, remote mic or emergency switch. Siren has priority over chime.

It is suitable for installation in schools, factories, hazardous areas etc.



### FEATURES

- ✓ 5 types of chimes and 2 siren
- ✓ Adjustable output volume
- ✓ Selectable output as balanced or unbalanced line
- ✓ Front panel switch activation or via remote trigger port

### TECHNICAL SPECIFICATIONS

Operating voltage	24V DC ; 0.5A
Power consumption	0.3A
Chime type	4 tone up, 4 tone down, 2 tone Ringing bell, Westminster
Siren type	Constant siren 8 KHz Wavy siren
External activation	Dry contact
Output	Line 1V
Output impedance	10 K unbalanced
Gain	+4 dB max
Dimensions (WxHxD)	482 x 44 x 180 mm
Weight	1.55 kg