

# AMPERES PM-1060

## 6-ZONE DESKTOP PAGING MICROPHONE



**PM1060** is a 6 zone paging microphone. It is suitable for small size installations, whether it is located at the rack itself or be installed at remote location.

It has all it needs to be installed in a commercial installation, running on 24V DC, illuminated ring at microphone and zone selection facility. Output level can be set to Mic or Line level with balanced signal for long distance audio broadcast.



### FEATURES

- ✓ Condenser gooseneck microphone with illuminated ring
- ✓ Pre and post announcement 4 tone chime
- ✓ Adjustable chime and mic volume with balanced mic / line output level
- ✓ Output level selection to mic or line signal to suit the input type of the pre-amplifier mixer
- ✓ 6 zone selection

### TECHNICAL SPECIFICATIONS

Power requirement	24V DC via D9 conn.
Power consumption	150 mA
Zone selection	6 and 12 zones with ALL CALL
Microphone	Condenser Mic : Cardioid
Output impedance	600 Ohm
Output level	1.2V ( line output ) / balanced mic (775 mV)
Output dry contact	nil
Output controls	Chime and Mic level
Audio connections	1/4" stereo phone jack
Switching connection	D15 connector
Operating distance	300m (recommended)
Chime	4 tone up and 4 tone down
Indicators	Mic ring, zone switch, ALL CALL
Frequency response	100 - 12 kHz ( +/- 3 dB ; 0 dB out )
S/N ratio	> 60 dB
Gooseneck mic length	400 mm
Dimensions ( WxHxD )	150 x 62 x 186 mm
Weight	800 grams