

AMPERES SQ-9815

SEQUENTIAL POWER SWITCHER



AMPERES SQ-9815 is suitable for applications in PA, Sound and AV system in which it manages the powering sequence of every equipment in orderly manner. It works to provide some degree of protection to the lifespan of equipment. It has internal surge protection to kill harmful incoming power spikes. An important tool that works to safely powering up your equipment with a touch of a button.



FEATURES

- ✓ 8 channel with 6A per channel
- ✓ Total load of 15A with surge protection
- ✓ Cascade 2 units to form 16 channel setup
- ✓ On / Off sequential switching
- ✓ Remote switching port via external noiseless contact
- ✓ AC output via IEC connectors with channel isolation via DIP switch
- ✓ Channel isolation via DIP switch
- ✓ Ch. 8 with delay Off option for 2 min ; suitable for video projector powering
- ✓ Lock mode to avoid incidental switching

TECHNICAL SPECIFICATIONS

Operating voltage	230 / 240V ac
Power consumption	50 mW (without load)
Output voltage	230 / 240V AC
Max load / channel	6A
Max total load	15A
Output connection	IEC female socket
Max cascade	2 unit : total 16 channels
Surge protection	L-N, L-E, N-E
Clamping voltage	870V ac
Turn on sequence	Step 1 to 8 incremental
Turn off sequence	Step 8 to 1 decremented
Step timing	2 seconds
Delay off option	Channel 8 via DIP switch
Delay off timer	2 minutes
Switch lock	Via front switch
Indicators	AC mains, Ch. ON, Lock
Dimension (WxHxD)	482 x 44 x 180 mm
Weight	2.82 kg (exclude accessories)