

AMPERES ZS-5602

6-ZONE SPEAKER SELECTOR UNINTERRUPTED



INTRODUCTION

ZS5602 shall be suitable for uninterrupted paging setup, i.e. when an announcement to a zone is made, other areas with BGM shall not be interrupted. This shall require two sets of amplifiers connected to the ZS5602, thus the system shall consist of two sources, one being BGM and the other as Paging.

Similarly to ZS5601 / ZS5121, paging zone can be remotely triggered and each zone shall have separate amp input - zone output terminals, thus making it flexible for amp-zone configuration.



FEATURES

- ✓ Available in 6 zones for BGM and 6 for Paging with ALL CALL
- ✓ Expandable or link multiple units to form more zones
- ✓ Remote zone triggering port via external paging mic
- ✓ Emergency paging mic triggering port with dry contact for volume controller overriding application
- ✓ Aux DC output for selected paging zone
- ✓ Suitable for 3 or 4 wire system

TECHNICAL SPECIFICATIONS

Operating voltage	24V DC ; 0.5A
Power consumption	10W ; 0.42A at ALL CALL
Insertion loss	0.5 dB max
Max load / channel	400W at 100V line
Number of zones	6
Amplifier inputs	6 BGM ; 6 Paging
Zone selection - BGM	Front panel switch
Zone selection - Paging	Front panel switch, remote
Indicators	Zone LED
Aux output voltage	24V DC ; 3A max / zone
Dimension (WxHxD)	482 x 44 x 180 mm
Weight	2.2 kg