

AMPERES PA-330

30W 100V LINE MINI AMPLIFIER



INTRODUCTION

Amperes **PA330** has higher rating of 30W 100V line which accepts unbalanced line input. It can be used as remote amplifier in a decentralized PA system. Among applications include classroom paging and paging for remote station.

Using TS6100 (step down module) shall allow PA330 to accept 100V line input and thereby a very large network of paging can be implemented in a wider area.



FEATURES

- ✓ Available in 10 or 20W 4 Ohm rating
- ✓ Adjustable volume control for volume pre-set
- ✓ Compact size for easy installations

TECHNICAL SPECIFICATIONS

Rating	30W 100V line
Operating voltage	230 - 240V ac
Power consumption	0.17 A
Input signal	Mono, unbalanced line
Input sensitivity	40 mV
Max input level	1.2 V
Input impedance	10 K Ohm
Frequency response	150 - 15 KHz
Controls	Input volume pre-set
Dimensions (WxHxD)	160 x 95 x 170 mm
Weight	2.8 kg